

VDB Computers B.V.

Vlakdissel 9
1648 HJ De Goorn
info@vdbcomputers.nl
0229-544704

PowerBeam 5AC-500 - 450+ Mbps

Artikelnummer: PBE-5AC-500

**€182,00**

Incl. 21% BTW

High-Performance airMAX ac Bridge Incorporating a dish reflector design with proprietary airMAX ac technology, the PowerBeam ac is ideal for CPE deplo...

High-Performance airMAX ac Bridge Incorporating a dish reflector design with proprietary airMAX ac technology, the PowerBeam ac is ideal for CPE deployments requiring maximum performance.

Specifications PowerBeam 5AC 500

Dimensions:

- Radome Excluded: 520 x 520 x 308 mm (20.47 x 20.47 x 12.13")

- Radome Included: 525 x 525 x 315 mm (20.67 x 20.67 x 12.40")

Weight:

- Radome Excluded: 2.35 kg (5.18 lb)

- Radome Included: 3.15 kg (6.95 lb)

Power Supply: 24V, 0.5A Gigabit PoE

Max. Power Consumption: 8.5W

Power Method: Passive PoE (Pairs 4, 5+; 7, 8 Return)

Supported Voltage Range: 20-26VDC

Gain: 27 dBi

Networking Interface: (1) 10/100/1000 Ethernet Port

Processor Specs: Atheros MIPS 74Kc, 720 MHz

Memory: 128 MB DDR2, 16 MB Flash

LEDs: (1) Power, (1) LAN, (4) WLAN

Signal Strength LEDs: Software-Adjustable to Correspond to Custom RSSI Levels

Mounting: Pole-Mount (Kit Included)

ESD/EMP Protection: Air: +/- 24 kV, Contact: +/- 24 kV

Operating Temperature: -40 to 70 C (-40 to 158 F)

Operating Humidity: 5 to 95% Noncondensing

Wireless Approvals: FCC, IC, CE

RoHS Compliance: Yes

Package Contents

Reflector, Radome, Antenna Feed, Rear Housing, Mounting Bracket, Adjustment Bracket, Hex Bolts with Washers (4), Pole Clamp (2), Carriage Bolts (4), Flange Nuts (4), Screws with Washers (4), Washers (4), Nylon Insert Lock Nuts (4), Gigabit PoE (24V, 0.5A) with Mounting Bracket, Power Cord, Quick Start Guide.

*

Indien dit product boven de toegestane limieten gebruikt wordt, is dit niet langer vergunningsvrij en zelfs illegaal (max zendvermogen: 100 mW op 2,4GHz en 200 mW op 5GHz). Wij raden u aan de standaard configuratie v.w.b. de landeninstelling en/of vermogensinstelling van de apparatuur niet te wijzigen. Het gebruik van meer dan het wettelijke toegestane vermogen kan leiden tot verminderde bruikbaarheid van WIFI in uw onmiddellijke omgeving.