

Vlakdissel 9
1648 HJ De Goorn
info@vdbcomputers.nl
0229-544704

Artikelnummer: PBE-5AC-GEN2



Incl. 21% BTW

Ubiquiti Networks launches the latest generation of airMAX CPE (Customer Premises Equipment), the PowerBeam 5AC Gen 2, with dedicated Wi-Fi management.

Improved Noise Immunity

The PowerBeam 5AC Gen 2 directs RF energy in a tighter beamwidth. With the focus in one direction, the PowerBeam 5AC Gen 2 blocks or spatially filters out noise, so noise immunity is improved. This feature is especially important in an area crowded with other RF signals of the same or similar frequency.

Integrated Design

Ubiquiti's InnerFeed technology integrates the radio into the feedhorn of an antenna, so there is no need for a cable. This improves performance because it eliminates cable losses. Featuring high performance and innovative design, the PowerBeam 5AC Gen 2 is versatile and cost-effective to deploy.

Management Wi-Fi Radio

The PowerBeam AC integrates a separate Wi-Fi radio for fast and easy setup using your mobile device (Android/iOS).

Specifications PowerBeam 5AC Gen 2

Dimensions: 420 x 420 x 230 mm (16.54 x 16.54 x 9.06")

Weight: 2.22 kg (4.89 lbs)

Power Supply: 24V, 0.5A Gigabit PoE Adapter (Included)

Max. Power Consumption: 8.5W

Power Method: Passive PoE (Pairs 4, 5+; 7, 8 Return)

Supported Voltage Range: 20 to 26VDC

Gain: 25 dBi

Networking Interface: (1) 10/100/1000 Ethernet Port

Processor Specs: MIPS 74Kc

Memory: 64 MB

LEDs: Power, Ethernet, (4) Signal Strength

Mounting: Pole-Mounting Kit (Included)

ESD/EMP Protection: Air: +/- 24 kV, Contact: +/- 24 kV

Operating Temperature: -40 to 70 C (-40 to 158 F)

Operating Humidity: 5 to 95% Noncondensing

RoHS Compliance: Yes

Certifications: CE, FCC, IC

Package Contents

Dish Reflector, Antenna Feed, Rear Housing, Adjustment Bracket, Mounting Bracket, Hex Bolts with Washers (4), Pole Clamp, Long Carriage Bolts (2), Flange Nuts (2), Gigabit PoE (24V,05A) with Mounting Bracket, Power Cord, Quick Start Guide

*

Indien dit product boven de toegestane limieten gebruikt wordt, is dit niet langer vergunningsvrij en zelfs illegaal (max zendvermogen: 100 mW op 2,4GHz en 200 mW op 5GHz). Wij raden u aan de standaard configuratie v.w.b. de landeninstelling en/of vermogensinstelling van de apparatuur niet te wijzigen. Het gebruik van meer dan het wettelijke toegestane vermogen kan leiden tot verminderde bruikbaarheid van WIFI in uw onmiddellijke omgeving.